

Rotary Phase Converter Electrical Specifications | Model size: 6000-225KW

TEMCo Heavy Duty Rotary Phase Converters provide utility quality 3-phase power converted from single phase power. TEMCo's world class products are being used throughout the US and internationally every day.

Common single to 3-phase conversion uses include:

- Machine Shops
- Woodworking
- Farm Equipment
- Restaurant Equipment
- Petrochemicals
- Home Hobbyist
- Oil Fields
- Irrigation
- High Tech
- Military
- Aerospace Industry
- Hospitals

TEMCo products meet the demands of tough industrial applications with dependability and quality.

Why choose TEMCo for your single to three phase needs?

- Run 3-phase equipment on single phase with a TEMCo Phase Converter.
- Rotary Higher quality lasts longer.
With minimal maintenance, requiring only periodic bearing grease, life expectancy is indefinite.
- TEMCo is a member of the Better Business Bureau.
TEMCo is a company you can trust.
- Quiet & smooth operation
TEMCo's Phase Converters are known for their unusually cool, smooth and quiet running characteristics.
- Every TEMCo Phase Converter carries a 6-Year Warranty.
In fact, it's the longest warranty available, unparalleled industry wide.
- Proudly Made in the U.S.A.

Table no. 1

Series 6000 Model Sizes

1-phase input voltage	208-240V or 440-480V *
1-phase input frequency	60 Hz
3-phase output voltage	= 1 phase Volts + 10% on L3 (non Loaded)
3-phase output frequency	60 Hz
3-phase output voltage tolerance	±10%
3-phase output phase angle	120°
Rating	40C amb.-cont.
Ambient humidity	<95% (non-condensing)
Maximum altitude	3300 ft above sea level (see note 2)
Enclosure	Type 1

Table no. 2

Model

	230V	460V
	6000-225KW	6000-225KW
Maximum Medium run or start HP	150 HP	150 HP
Maximum Hard run or start HP	100 HP	100 HP
Maximum recommended group load HP	200 HP	200 HP
Continuous 3-phase output amps		
Peak 3-phase output amps		
Peak kW output		
Peak 1-phase amps required		
Approximate 1-phase idle amps		
1-phase breaker recommended		
1-phase fuse recommended		
Recommended 1-phase wire size		
Recommended 3-phase wire size		

Specifications to be determined per application



* The default factory voltage configuration in this model is 208-240V. Units to be operated on 440-480V are built to order.

Note 1: Use only non time-delay fuses to protect this TEMCo Phase Converter

Note 2: De-rate TEMCo Phase Converter 20% for installation above 3300 feet altitude.

Note 3: Based on maximum loaded output.

Call to order

Inside USA:
(800) 613-2290

USA & International:
(510) 490-2187

Fax:
(510) 490-1507

web:
www.phaseconverter.com

e-mail:
info@phaseconverter.com