

## Rotary Phase Converter Electrical Specifications | Model size: 7000-7

TEMCo Heavy Duty Rotary Phase Converters provide utility quality 3-phase power converted from single phase power. TEMCo's world class products are being used throughout the US and internationally every day.

### Common single to 3-phase conversion uses include:

- Machine Shops
- Woodworking
- Farm Equipment
- Restaurant Equipment
- Petrochemicals
- Home Hobbyist
- Oil Fields
- Irrigation
- High Tech
- Military
- Aerospace Industry
- Hospitals

TEMCo products meet the demands of tough industrial applications with dependability and quality.

### Why choose TEMCo for your single to three phase needs?

- Run 3-phase equipment on single phase with a TEMCo Phase Converter.
- Rotary Higher quality lasts longer. With minimal maintenance, requiring only periodic bearing grease, life expectancy is indefinite.
- TEMCo is a member of the Better Business Bureau. TEMCo is a company you can trust.
- Quiet & smooth operation TEMCo's Phase Converters are known for their unusually cool, smooth and quiet running characteristics.
- Every TEMCo Phase Converter carries a 6-Year Warranty. In fact, it's the longest warranty available, unparalleled industry wide.
- Proudly Made in the U.S.A.

Table no. 1	Series 7000 Model Sizes	
1-phase input voltage	208-240V or 440-480V *	
1-phase input frequency	60 Hz	
3-phase output voltage	= 1 phase Volts + 5% on L3 (non Loaded)	
3-phase output frequency	60 Hz	
3-phase output voltage tolerance	±5%	
3-phase output phase angle	120°	
Rating	40C amb.-cont.	
Ambient humidity	<95% (non-condensing)	
Maximum altitude	3300 ft above sea level (see note 2)	
Enclosure	Type 1	

Table no. 2	Model	
	230V 7000-7	460V 7000-7
Continuous 3-phase output amps	12.2 amps	6.1 amps
Continuous kW output	3.7 kW	3.7 kW
Peak 1-phase amps required	21.1 amps	10.5 amps
Approximate 1-phase idle amps	5 amps	2.5 amps
1-phase breaker recommended	25 amps	10 amps
1-phase fuse recommended	25 amps (see note 1)	12 amps (see note 1)
Recommended 1-phase wire size	10 AWG	14 AWG
Recommended 3-phase wire size	14 AWG	14 AWG



\* The default factory voltage configuration in this model is 208-240V. Units to be operated on 440-480V are built to order.

**Note 1:** Use only non time-delay fuses to protect TEMCo series 7000 Phase Converters

**Note 2:** De-rate TEMCo Phase Converter 20% for installation above 3300 feet altitude.

### Call to order

Inside USA: (800) 613-2290	USA & International: (510) 490-2187	Fax: (510) 490-2187	web: www.phaseconverter.com	e-mail: info@phaseconverter.com
-------------------------------	----------------------------------------	------------------------	--------------------------------	------------------------------------